

Nervous LEDMAN



A small analog, interactive

light object that responds to sounds and vibrations by flashing a LED.

It's very sensitive, and reacts on human voice over a distance of 3m or more, when put on the right

surface, e.g. a wooden table, box or anything that vibrates.

Nervous LEDMAN consists of 3 parts : (top down)

1) battery holder & power switch

I use a [LilyPad coin battery holder](#) or compatible and a rechargeable LIR2032 battery

2) LEDMAN PCB

It's a redesign of a [circuit by Yair Reshef](#) .

The original design uses an obsolete opamp and needs 2 batteries for 6V supply. Now it runs with a single cell and uses a cheap standard opamp + 3 resistors + 1 ceramic capacitor in "beginner friendly" sized SMD packages (1206)

3) piezo disc sensor

this is a common 35mm diameter Piezo sounder/buzzer/speaker/drum sensor. Smaller discs are not recommended until you put LEDMAN straight on a loudspeaker box ;-)

the picture shows the "elektro kitsch" (C) version with vintage power resistors as legs and arms. A flexible 38mm, 3V LED filament is used as LED.

construction notes :

resistor "arms" can be 0...10 Ohm, any wattage.

resistor "legs" can be 0...100 Ohm, any wattage.

LilyPad connection is a bit tricky : the red "+" wire is soldered straight to a LilyPad "+" pin. The black "-" wire tunnels the other LilyPad "+" pin without connection (it must be isolated) and is soldered to LilyPad "-" pin on the rear side.

The reason is: if you solder a wire to one of LilyPads "-" pins on the battery side, the battery can't be removed anymore !

documentation :

schematics : [NervousLEDMAN_SCH.pdf](#)

SMD assembly : [NervousLEDMAN_ASY.pdf](#)

credits go to my friend Yair Reshef and unknown early developers for inspiration
and Leah Buechley for LilyPad
respect CC NC BY SA

Revision #7

Created 11 June 2023 07:57:07 by ElektroUwe

Updated 12 March 2025 13:58:40 by ElektroUwe